

## DM837 High Fidelity Digital Player with Amplifier



### *Description*

DM837 is suitable for small venues like apartment, office room and retail shops. Three color options: black white and brown. With 3.5" TFT capacitance touch screen, it can display functions very clearly and have accurate control. It has abundant audio source such as FM, SD, BT and AUX. It's quick and convenient to play music. It can be equipped with a infrared remote controller so that users can control the music easily when they sit on the sofa.

## Features

- Music control center, convenient and easy-operating.
- Luxurious design, 3.5-inch TFT LCD screen, capacitive touch operation.
- Four connection modes: FM radio, USB / SD, BLUETOOTH, AUX.
- MP3, WAV, FLAC and other compressed, lossless audio formats.
- Auxiliary input sensitivity (adjustable).
- FM radio support, automatic, manual collection, 20 channels storage.
- Wide voltage input, fit in with 100 ~ 240VAC, 50 / 60Hz
- Class D differential output.
- Infrared remote control operation.
- RS485 control.

## Specification

Power Supply Input	100-240V/50/60Hz
Output Power	2 ×10W
Rated Impedance	8Ω
Total Harmonic Distortion	≤0.03% (1KHz, 1W, 8Ω)
Signal to Noise Ratio	>81dB
Frequency Response	20Hz – 20KHz
Auxiliary input sensitivity (adjustable)	AUX: 1.0V / 500mV
Audio format	MP3, WAV, FLAC
Bluetooth input	BT4.1
Control interface	RS485
Storage type	SD card, USB
Product size	86×86×38mm
Remote control effective infrared angle	60°
Effective remote control distance	8-12m
Remote control battery	CR2032