

## WiReless Alarm sèstem elegant pro series





Your Security is Our Passion



## ST-02R Stark Emergency button SOS

## **Features:**

Emergency button detector, once the emergency incident occurs, the detector will be triggered to transmit the signal to the alarm system.

This product is suitable for all the places where the security protection is needed, such as residential areas, companies, shopping malls, hospitals, banks, guard post etc.

- Double alarm types, button type and pull type.
- Compact appearance, can hang it up.
- Anti-false alarm design.
- Zero standby power consumption.
- Low-battery detection.
- MCU coding, compatible with 2262/1527.
- Anti RFI (20V/m-1GHz).
- SMT process.

## TECHNICAL SPECIFICATION



Power	3V (1*CR2032 button cell)	Working Environment	10°C <b>~</b> +50°C
Standby Current	0 μΑ	<b>Emission Distance</b>	50m - 100m (open area)
Dimension (L*W*H)	38*58*15mm	Humidity	< 80%RH (no congelation)
Alarm Current	≤25mA	Transmitting Frequency	315Mhz or 433Mhz
Alarm Indicator	Red LED	Alarm Type	Button type and pull type