

TAKTIS® UL VISION

Annunciator

Features

- Full-color 7" (800 x 480 pixel) interface
- Replicates information displayed at the FACP
- Automatic display brightness adjustment
- Internal buzzer
- > Connects via control panel network terminals
- ▶ Low current, 24V DC powered

- ► Configurable functionality
- Enable key-switch
- Sheet steel enclosure
- > Surface or semi-flush options available



Description

Taktis UL Vision Annunciator provides a means of allowing full display and optional control of the Taktis UL Fire Alarm control panel from a small and unobtrusive local control station.

The large, full colour graphical display with touch screen functionality, delivers information on the status of the fire alarm system to single or multiple locations. Taktis Vision repeaters can be configured to offer full display and control to replicate the functionality of the Fire Control panel or to operate as a simple, display only device for applications where access to control the Fire Alarm system would be inappropriate.

Taktis Vision may be connected to the fire control panels' fault tolerant RS485 network using standard, fire rated cable offering flexibility in system wiring.

Available in several standard formats, Taktis Vision can be mounted directly onto a wall, be recessed using our quick-fix adaptor frame or semi-flush mounted.

Specification		
Construction	1.2mm mild sheet steel	
IP Rating	IP30	
Finish	Epoxy powder coated	
Colour - Lid & Box	BS oo A o5 grey (fine texture) or Red RAL3002	
Weight	2KG	
Display	Full colour 800 x 480 LCD with resistive touch screen and automatic backlight dimming	
Supply voltage range	21 to 30 V DC	
Quiescent current consumption	253mA typical (buzzer off @ 24V DC) 301mA typical (buzzer on @ 24V DC) 341mA max (buzzer on @ 21V DC)	
RS485 fire panel network	Taktis is approved for networks of up to 32 panels (Approval for networks of up to 127 panels pending)	

Panels		
Product Code	Description	Size (mm)
TRCooNC-10	Taktis Vision - Surface, Red enclosure finish	235W x 170H x 55D
TRCooNC-40	Taktis Vision - Surface, Gray enclosure finish	235W x 170H x 55D
KM1098RD	Taktis Vision - Flush mount adaptor frame, Red finish	n/a
KM1098GY	Taktis Vision - Flush mount adaptor frame, Gray finish	n/a



Datasheet DS123/07/21 Rev.02

For further information visit www.kentec.co.uk Kentec Electronics Ltd. reserves the right to alter the specification of its products from time to time without notice. Although every effort has been made to ensure the accuracy of the information contained in this document it is not warranted or represented by Kentec Electronics Ltd. to be a complete and up-to-date description.